



Bravo 501

Numeric Pager



MESSAGE CAPACITY

- 20 numeric message capacity

MESSAGE STORAGE AND PROTECTION

- Allows user to store/lock 10 messages

ADDRESS CAPCODE

- Receives up to 4 addresses, including 1 personal and 3 group call addresses

DISPLAY FORMAT

- Shows 1 line of 12 characters plus 1 line of icons

TIME AND DATE DISPLAY

- Real-time display for convenient reference

MESSAGE TIME STAMPING

- Shows when messages were received

'DELETE MESSAGE' OR 'DELETE ALL' MESSAGE OPTIONS

- Allows user to delete a single unlocked message or all unlocked stored messages

MELODY/TONE ALERTS

- Allows user to choose from 12 alerts PLUS 'vibrate' and 'silent/no alert' options

tone ALERT TIME

- Tone plays for 8 seconds

BUILT IN ALARM CLOCK

- Choice of 3 alarm settings

REMINDER ALERT

- User selectable option informs and alerts the user that a message is unread and waiting

DISPLAY BACKLIGHT

View messages in low light conditions

BATTERY

- 1 AAA battery (1.5 V) required

BATTERY GAUGE

- Shows when the battery is getting low

LOW BATTERY ALERT

- Indicates when the battery power is low

BATTERY BACK UP

- Retains unlocked messages for 30 seconds during battery replacement

WEIGHT

- 1.6 oz.

SIZE

- 2 1/2 "L x 1 1/2 "H x 1/2 "W

COLOR

- Black

SPECIFICATIONS

Frequency Range	929-932 MHz
Format	1600/ 3200/ 6400 FLEX
Operating Temp	23°F – 104°F (-5°C to 40°C)
Alert Tone Loudness	75 dB @ 12 inches (30 cm)

For more information, please contact your Arch Wireless representative or call 1-888-960-2724

