

# Br502 Numeric Pager



## The Br502 numeric pager

offers on-the-go professionals a reliable and convenient way to stay connected wherever business or life takes them.

With its easy-to-use two-button design, scratch-resistant lens, and removable belt clip, the Br502 delivers the durability and functionality required to meet all your messaging needs.

## Features Include:

- Convenient Two-Button Design
- Scratch Resistant Lens
- Removable Belt Clip
- Up to 18 Personal Memory Slots
- Daily Alarm
- Private Time
- Backlight
- 8 User-Selectable Alerts

Contact Arch Wireless for more information:

Email: [solutions@arch.com](mailto:solutions@arch.com)

Phone: 866-206-0810

Web: [www.arch.com](http://www.arch.com)



# Br502 Features

The Br502 pager offers the latest enhanced features to help you stay connected.

## Message Capacity

- Can receive up to 18 personal messages

## Message Storage and Protection

- Locks/saves up to 10 messages

## Address Capcode

- Stores up to 8 personal or group capcodes

## Display Format

- Shows 1 line of 12 characters (9 segment display) plus one line of icons

## Time and Date Display

- Real time display in 12 or 24 hour format

## Message Time Stamping

- Shows when messages were sent/received

## Melody/Tone Alerts

- Choose from 8 melody alerts, as well as chirp, vibrate, vibrate/chirp and silent/no alert options

## Private Time

- Preset times to automatically turn alert sounds on/off

## Alarm Clock

- Set a daily reminder for important events

## Reminder Alert

- Set reminder alerts every 2 minutes until all new messages are read

## Message Indicators

- Continuous Message Indicator directs user to scroll down to read entire message.
- Error Message Indicator alerts user to possible error in message

## Memory Indicator

- Alerts user when message capacity is full and messages will be deleted from oldest to newest

## Display backlight

- View messages in low light conditions

## Battery and Battery Back Up

- Retains messages for 30 seconds while battery is changed

## Battery Level Indicator

- Displays remaining power level and chirps to alert user of low battery level

## Removable Beltclip

- Remove the belt clip for added convenience

---

## SPECIFICATIONS

Frequency Range	929-932 MHz	Weight	1.5 oz. with battery
Code Format	1600/3200/6400 FLEX	Size	1 5/8L x 2 3/8H x 5/8W inches
Operating Temp	14°F (-10°C) to 104°F (40°C)	Battery Type	1 x Alkaline AAA
Alert Tone Loudness	75 dB SPL at 12 inches	Battery Life	Estimated 70 days
		Color	Black

